

Горизонтальные многоступенчатые центробежные насосы CMF

Технические характеристики

По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +(727)345-47-04

Беларусь +(375)257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: axh@nt-rt.ru || сайт: <https://lx.nt-rt.ru>



LX CMF2-30 CMF2-50 CMF2-60 Horizontal Multistage Centrifugal Pump, LX Stainless Steel Centrifugal Pump:

(LX Pump: Top Quality Pump In China)

1) Feature:

Stainless Steel Centrifugal Pump: CMF series is pump casing-oriented multistage stainless steel pump; the liquid part is made of SUS304,. Under processing of advanced welding equipment, heat treatment, the stress caused by end-cut plate in tension and press forming is eliminated to make in high strength, no deformation, long life, safe and reliable usage; Applied mechanical seal type ensure watertight in long-time continuous operation. The material of frame is aluminum; it is under low-noise and less-vibration and durability. Insulation class B, Protection IPX55, continuous duty; Single-phase with thermal protector from T1 to ensure safety and convenience.

Certificate: 1. China CCC certificate

2. TUV certificate Germany

2) Application:

1. Air-conditioning system
2. Water treatment
3. Pressure boosting for the water on processing line.
4. Heating and cooling water on industrial processing line
5. Air freshen, moistening equipment (soft water)
6. Water supply and pressure boosting (drinking water, weak chlorine water)
7. Fertilization/metering system
8. Aquaculture
9. Convey thin, clean, non-flammable and non-explosive liquid without solid granules and fibers

3) Operation conditions:

1. Liquid temperature: $+5^{\circ}\text{C}$ - $+60^{\circ}\text{C}$
2. Max ambience temperature: $+50^{\circ}\text{C}$
3. Max pressure: 10 bar
4. Max suction head: No self-priming
5. Maximum inlet pressure is limited by the maximum operating pressure

4) Guide for model selection:

1. Request for the flow and pressure

2. The mechanical seal configurations is selective for normal water, pure water or hot water type.

3. Applied region's voltage and frequency: single-phase: 220-240V/50Hz ; 220V-240V/60Hz ; 110-120V/60Hz is available; three-phase: 380-415V/50Hz ; 380-415V/60Hz is available.

4. Applied region's request for safety certific4. Confirm the bore of outlet and inlet.

5. Plug's type and length (no plug, Chinese plug, Europe plug, UL plug is available)

1. CMF2 series

model		power P2 (kw)	Q (m ³ /h)	1.0	1.5	2.0	2.5	3.0	3.5	Packing size	(kg)
220V/50Hz	380V/50Hz										
CMF2-20	CMF2-20T	0.37	H (m)	18	16	14	13	11	10	435*215*290	9.0
CMF2-30	CMF2-30T	0.37		27	24	21	20	17	14	435*215*290	9.5
CMF2-40	CMF2-40T	0.55		35	32	38	26	23	17	435*215*290	10
CMF2-50	CMF2-50T	0.55		43	40	35	33	28	22	435*215*290	10
CMF2-60	CMF2-60T	0.75		50	48	42	38	32	25	435*215*290	10.5

2. CMF4 series

model		power P2 (kw)	Q (m ³ /h)	2.0	3.0	4.0	5.0	6.0	7.0	Packing size	(kg)
220V/50Hz	380V/50Hz										
CMF4-20	CMF4-20T	0.55	H (m)	18	16	15	13	10	7	435*215*290	10
CMF4-30	CMF4-30T	0.75		27	25	22	19	15	10	435*215*290	11
CMF4-40	CMF4-40T	0.75		36	33	30	26	20	14	435*215*290	11.5
CMF4-50	CMF4-50T	1.0		44	41	38	32	26	20	435*215*290	12
CMF4-60	CMF4-60T	1.1		53	50	45	40	33	24	435*215*290	12.5

3. CMF8 series

model		power P2 (kw)	Q (m ³ /h)	4.0	5.0	6.0	7.0	8.0	9.0	10	Packing size	(kg)
220V/50Hz	380V/50Hz											
CMF8-10	CMF8-10T	0.55	H (m)	15	14	13	12	10	9	8	490*275*315	10.5
CMF8-15	CMF8-15T	0.75		25	23	22	20	17	14	12	490*275*315	12.0
CMF8-20	CMF8-20T	1.0		30	28	26	24	20	18	16	490*275*315	14.0
CMF8-25	CMF8-25T	1.5		43	37	34	30	27	24	20	490*275*315	17.0
CMF8-30	CMF8-30T	1.85		44	42	38	36	30	27	24	490*275*315	21.5
CMF8-35	CMF8-35T	2.2		56	51	48	44	37	32	28	490*275*315	23.0

4. CMF12 series

model		power P2 (kw)	Q (m ³ /h)	6.0	7.0	8.0	9.0	10	11	12	13	14	Packing size	(kg)
220V/50Hz	380V/50Hz													

CMF12-10	CMF12-10T	1.0	H (m)	19	18	17.5	16	15.5	14	13.5	12	10.5	490*275*315	12.0
CMF12-15	CMF12-15T	1.5		28	27	26	25	24	22	20	18	15	490*275*315	13.5
CMF12-20	CMF12-20T	1.85		38	36	35	32	31	29	28	24	20	490*275*315	21.0
CMF12-25	CMF12-25T	2.2		47	45	43	41.5	39	36	33.5	30.5	27	490*275*315	24.0
*	CMF12-30T	3.0		53.5	52	50	47.5	45	42	39	35	30	550*275*300	27.0

5. CMF16 series

model		power P2 (kw)	Q (m ³ /h)	8	10	12	14	16	18	20	22	24		(kg)
220V/50Hz	380V/50Hz													
CMF16-10	CMF16-10T	1.0	H (m)	12	11.5	11	10.5	10	9	8	7	6		13.5
CMF16-20	CMF16-20T	1.5		24	23	22	21	20	19	16	14	12		17
CMF16-30	CMF16-30T	2.2		38	36	34	33	30	28	26	23	20		23

6. CMF20 series

model		power P2 (kw)	Q (m ³ /h)	10	12	14	16	18	20	22	24	26	28		(kg)
220V/50Hz	380V/50Hz														
CMF20-10	CMF20-10T	1.0	H (m)	13	12.5	12	11.5	11	10.5	10	9	8.5	7.5		20
CMF20-20	CMF20-20T	1.85		25	24	23	22	21	20	18	16	14	12		22
*	CMF20-30T	3.0		39	38	36	35	33	31.5	30	27	24	21		25

По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +(727)345-47-04

Беларусь +(375)257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: axh@nt-rt.ru || сайт: <https://lx.nt-rt.ru>